

Raspberry Pi GPIO

3.3V			5V
SDA			5V
SCL			GND
GPCLK0			TXD
GND			RXD
11			PCM CLK
PCM D.out			GND
15			16
3.3V			18
MOSI			GND
MISO			22
SCLK			CE0
GND			CE1

Model B Rev 2 (Nox Miles.de)

3V3			5V
2			5V
3			GND
4			TXD >
GND			RXD <
17			18
27			GND
22			23
3V3			24
MOSI			GND
MISO			25
SCLK			CE0
GND			CE1

Model B Rev 2 (Raspi Foundation)

1			2
3			4
5			6
7			8
9			10
11			12
13			14
15			16
17			18
19			20
21			22
23			24
25			26

Model B Rev 2 (Pin #)

3V3			5V
GPIO2 SDA			5V
GPIO3 SCL			GND
GPIO4			GPIO14 TXD
GND			GPIO15 RXD
GPIO17			GPIO18
GPIO27			GND
GPIO22			GPIO23
3V3			GPIO24
GPIO10 MOSI			GND
GPIO9 MISO			GPIO25
GPIO11 CLK			GPIO8 CE0
GND			GPIO7 CE1

Model B Rev 2 (Developer-blog.net)

3.3V			5V
2 SDA			5V
3 SCL			GND
4			14 TXD
GND			15 RXD
17			18
27			GND
22			23
3.3V			24
10 MOSI			GND
9 MISO			25
11 SCLK			8
GND			7

Model B Rev 2 (doctormank.com)

	1	2
	3	4
	5	6
	7	8
	9	10
	11	12
	13	14
	15	16
	17	18
	19	20
	21	22
	23	24
	25	26

26 Pin GPIO

3.3V			5V
SDA			5V
SCL			GND
GPCLK0			TXD
GND			RXD
11			PCM CLK
PCM D.out			GND
15			16
3.3V			18
MOSI			GND
MISO			22
SCLK			CE0
GND			CE1
ID_SD			ID_SC
29			GND
31			32
33			34
35			36
37			38
GND			40

Model B+ (Nox Miles.de)

3V3			5V
SDA			5V
SCL			GND
GPIO4			TXD
GND			RXD
GPIO17			PCM CLK
GPIO27			GND
GPIO22			GPIO23
3V3			GPIO24
MOSI			GND
MISO			GPIO25
SCLK			CE0
GND			CE1
ID_SD			ID_SC
GPIO5			GND
GPIO6			GPIO12
GPIO13			GND
GPIO19			GPIO16
GPIO26			GPIO20
GND			GPIO21

Model B+ (raspberrypi-spy.co.uk)

	1	2
	3	4
	5	6
	7	8
	9	10
	11	12
	13	14
	15	16
	17	18
	19	20
	21	22
	23	24
	25	26
	27	28
	29	30
	31	32
	33	34
	35	36
	37	38
	39	40

40 Pin GPIO